

Signal Level Control Model SLC



Description The SLC is a continuously variable volume control that can remotely control the volume of up to 150 self-amplified speakers. The SLC fits into a single gang electrical box.

- Features**
- Remotely control the volume of up to 150 self-amplified speakers
 - Rugged and attractive stainless steel plate with engraved lettering
 - Mounts in a single gang electrical box
 - Easy and secure terminal strip connections
 - Passive (requires no DC power)
-

Technical Specifications Max. Speaker Capacity: 150
Dimensions: 2-7/8" W x 4-5/8" H x 2" D
Product Weight: 2 oz.

Architect & Engineer Specifications The Level Controller shall be a continuously variable passive volume control that can remotely control the volume of up to 150 self-amplified speakers, Bogen Model SLC. The SLC output terminals shall be able to control up to 150 speaker inputs. Output wiring shall be made via two separate two-position screw terminal blocks for input and output signals.

The SLC shall have a rugged and attractive stainless steel plate with engraved lettering.

The SLC shall measure 2-7/8" W x 4-5/8" H x 2" D and fit into a single gang electrical box. The SLC shall weigh 2 ounces.

BOGEN[®]
COMMUNICATIONS, INC.

50 Spring Street, Ramsey, NJ 07446, U.S.A.
Tel.: 201-934-8500 • Fax: 201-934-9832
www.bogen.com